

WHAT IS CLAIMED IS:

1. A system for packet arrival time detection, comprising:  
a receiver configured to receive a signal;  
5 a packet arrival time detector, coupled to the receiver, configured to  
produce a packet arrival time output; and  
a power estimator, coupled to the receiver, configured to estimate the  
power in the received signal and provide the estimated power to the  
packet arrival time detector to validate the packet arrival time  
10 output.
2. The system of claim 1, wherein the power estimator includes a squaring  
device configured to square the received signal to produce the estimated power  
of the received signal.  
15
3. The system of claim 2, wherein the power estimator includes a bandpass  
filter configured to filter the received signal and to provide the filtered received  
signal to the squaring device.
- 20 4. The system of claim 2, wherein the power estimator includes a lowpass  
filter configured to filtered the output of the squaring device to produce a  
filtered power estimate of the received signal.

5. The system of claim 1, wherein the power estimator includes a Hilbert transform configured to produce an analytic signal comprising a real component and an imaginary component.

5 6. The system of claim 5, wherein the real component of the analytic signal is the received signal and the imaginary component of the analytic signal is the quadrature signal of the received signal.

7. The system of claim 5, wherein the power estimator includes a bandpass  
10 filter configured to filter the received signal and to provide the filtered received signal to the Hilbert transform.

8. The system of claim 7, wherein the bandpass filter is configured to have  
a frequency response with notches at frequencies where narrow band  
15 interference is present.

9. The system of claim 5, wherein the power estimator includes a first  
squaring device configured to square the real component of the analytic signal,  
a second squaring device configured to square the imaginary component of the  
20 analytic signal, and an adder configured to add the squared real component  
and the squared imaginary component to produce the estimated power.



16. The method of claim 15, wherein the step of processing the received signal to produce an estimated power further includes lowpass filtering the squared bandpass-filtered received signal to produce the estimated power.

5

17. The method of claim 13, wherein the step of processing the received signal to produce an estimated power includes Hilbert transforming the received signal to produce an analytic signal with a real component and an imaginary component.

10

18. The method of claim 17, wherein the real component of the analytic signal is the received signal and the imaginary component of the analytic signal is a quadrature signal of the received signal.

15

19. The method of claim 18, wherein the quadrature signal of the received signal is a Hilbert transform of the received signal.

20

20. The method of claim 17, wherein the step of processing the received signal to produce an estimated power includes bandpass filtering the received signal and providing the filtered received signal to the Hilbert transform.

21. The method of claim 20, wherein the bandpass filtering of the received signal removes narrow band interference.



27. A system for packet arrival detection, comprising:  
means for receiving a signal;  
means for processing the received signal to produce a packet arrival time  
output;  
5 means for processing the received signal to produce an estimated power;  
and  
means for validating the packet arrival time output using the estimated  
power.

10 28. A system for packet arrival time detection, comprising:  
a receiver configured to receive a signal;  
a packet arrival time detector, coupled to the receiver, configured to  
produce a packet arrival time output;  
a power estimator, coupled to the receiver, configured to determine an  
15 estimated power of the received signal and to provide the estimated  
power to the packet arrival time detector to validate the packet  
arrival time output, where the power estimator generates an  
analytic signal including a real component equal to the received  
signal and an imaginary component equal to a Hilbert transform of  
20 the received signal, and the power estimator squares the real and  
imaginary components of the analytic signal and adds together the  
squared real and imaginary components of the analytic signal to  
produce the estimated power.

29. The system of claim 28, wherein the power estimator bandpass filters the received signal to remove narrow band interference prior to generating the analytic signal.

5

30. The system of claim 29, wherein the power estimator lowpass filters the estimated power prior to providing the estimated power to the packet arrival time detector.

10